วิธีการแก้ไขติดตั้งไดร์เวอร์สแกนไม่ได้ (การเปิด Service Shell Hardware Detection) สำหรับ Windows

รองรับปริ้นเตอร์รุ่น : ทุกรุ่นที่ใช้งานผ่านไดร์เวอร์ หรือ ชอฟท์แวร์ Epson Scan

เมื่อ Shell Hardware Detection ถูก Disable หรือ ขึ้นเออเรอร์

"Error Could not launch required program during setup, check the setup disc, then run setup again."



ให้ทำการ เปิด Service Shell Hardware Detection วิธีการมีดังนี้

1.ไปที่ **Control Panel**



2.ไปที่ Administrative Tools



3.ดับเบิ้ล คลิก **Services**

Control Panel All Control Panel Items Administrative Tools furn					
	B: Component Services	7/14/2009 12:46 AM			
	🚰 Computer Management	7/14/2009 12:41 AM			
	Data Sources (ODBC)	7/14/2009 12:41 AM			
15	desktop.ini	9/27/2010 5:08 PM			
	Event Viewer	7/14/2009 12:42 AM			
	😥 iSCSI Initiator	7/14/2009 12:41 AM			
	Local Security Policy	9/27/2010 5:08 PM			
	Performance Monitor	7/14/2009 12:41 AM			
	Print Managerget	9/27/2010 5:08 PM			
	Services	7/14/2009 12:41 AM			
	System Configuration	7/14/2009 12:41 AM			
	🛞 Task Scheduler	7/14/2009 12:42 AM			
	Windows Firewall with Advanced Security	7/14/2009 12-41 444			

4.ดับเบิ้ลคลิก Shell Hardware Detection

Services						
File Action View	<u>H</u> elp					
	à 🛃 📝 📷 🕨 🔲 II IV					
Services (Local)	Services (Local)					
	Shell Hardware Detection	Name	Description	Status	Startup Type	Log On As 🔺
	Description: Provides notifications for AutoPlay hardware events.	 Remote Access A Remote Access C Remote Procedur Remote Procedur Remote Registry Routing and Rem Secondary Logon Secure Socket Tun Security Accounts Security Center 	Creates a co Manages di Serves as th Manages th Enables rem Offers routi Enables star Provides su The startup Monitors sy	Started Started Started Started Started Started	Manual Manual Automatic Manual Disabled Automatic Manual Automatic Automatic (D	Local Syste Local Syste Network S Network S Local Service Local Syste Local Syste Local Syste Local Syste Local Service
		Shell Hardware De	Provides no		Disabled	Local Syste ≡
		🔍 SL UI Notification	Provides So		Manual	Local Service
		🎑 Smart Card	Manages ac		Manual	Local Service
		Smart Card Remo	Allows the s		Manual	Local Syste
		SNMP Trap	Receives tra	.	Manual	Local Service
		Software Licensing	Enables the	Started	Automatic	Network S
		SQL ACTIVE DIFECT	Drovides sto	Started	Automatic	Network S
		SOL Server Agent	Executes io	Junea	Disabled	Network S
			<u>n : 1 co</u>		D: 11 1	· · · · ·
	Landed (Standard (•		111		•

5.เลือก Startup type เป็น Automatic จากนั้นกด Apply แล้วกด OK

Shell Hardware Detection Properties (Local Computer)							
General Log On	Recovery Dependencies						
Service name:	ShellHWDetection						
Display <u>n</u> ame:	Shell Hardware Detection						
Description:	Provides notifications for AutoPlay hardware events.						
Pat <u>h</u> to executable C:\Windows\Syste	Pat <u>h</u> to executable: C:\Windows\System32\svchost.exe -k netsvcs						
Startup type:	Disabled						
Help me configure	Automatic (Delayed Start) Help me configure Automatic Manuai						
Service status:	Disabled Stopped						
Start	Stop <u>P</u> ause <u>R</u> esume						
You can specify the start parameters that apply when you start the service from here.							
Start parameters:							
	3 2						
OK Cancel Apply							