้วิธีการติดตั้งไดร์เวอร์เครื่องพิมพ์ รุ่น L655 เชื่อมต่อแบบ USB สำหรับ Mac OSX

หมายเหตุ : สำหรับการติดตั้งแบบ USB แนะนำให้ทำการโหลดไดร์เวอร์ก่อนดังนี้

1.เข้าเวปลิ้งค์

http://www.epson.co.th/epson thailand/ink tank system printers/product.page?product name=Epson L655



2.ดูที่ Choose your operating system for drivers? เลือก Mac OS X – Intel [1] > คลิก Drivers & Software [2] > เลือกไดร์เวอร์ Printer Driver กด Download [3]

EPSON L655	OVERVIEW 1	TECH SPECS	INK & ACCESSORIES	DRIVERS & SUPPORT
Drivers & Support: Epson L	655			
Choose your operating system for drivers? Mac OS X - Intel v				
Drivers & Software 2				
Drivers				
Printer Driver		Download	3	
Scanner Driver		Download		

3.จะได้ไฟล์สำหรับการติดตั้งมา



4.ดับเบิ้ลคลิกที่ EPSON Printer.pkg

5.คลิกที่ **Continue**



6.คลิกที่ **Continue**

	🤤 Install EPSON Printer Driver			
	Software License Agreement			
	English			
Introduction	SEIKO EPSON CORPORATION			
License	SOFTWARE LICENSE AGREEMENT			
Destination Select	IMPORTANT! READ THIS SOFTWARE LICENSE AGREEMENT CAREFULLY. The computer software product, fontware, typefaces and/or data, including any accompanying explanatory written materials (the "Software") should only be installed or used by the Licensee ("you") on the condition you agree with SEIKO EPSON CORPORATION ("EPSON") to the terms and conditions set forth in this Agreement. By installing or using the Software, you are representing to agree all the terms and conditions set forth in this Agreement. You should read this Agreement carefully before installing or using the Software. If you do not agree with the terms and conditions of this Agreement, you are not permitted to install or use the Software.			
Installation Type				
Installation				
Summary				
	1. License. EPSON and its suppliers grant you a personal, nonexclusive, royalty-free, non-sublicensable limited license to install and use the Software on any single computer or computers that you intend to use directly or via network. You may allow other users of the computers connected to the network to use the Software, provided that you (a) ensure that all such users agree and are bound by the terms and conditions of this Agreement, (b) ensure that all such users use the Software only in conjunction with the computers and in relation to the network of which they form part, and (c) indemnify and keep whole EPSON and its suppliers against all damages, losses, costs, expenses and liabilities which EPSON or its suppliers may incur as a consequence of such users failing to observe and perform the terms and conditions			
	Print Save Go Back Continue			

7.คลิกที่ Agree





9.จะขึ้นหน้าต่างให้ใส่ Password (ถ้ามี) และคลิก Install Software

Installer is your passw	trying to install new software. Type ord to allow this.
Username:	HotLine
Password:	•••••
	Cancel Install Software

10.จะปรากฎหน้าต่างดังรูป

0 0	Install EPSON Printer Driver	
	Installing EPSON Printer Driver	
 Introduction License Destination Select Installation Type Installation Summary 	Optimizing system for installed software Install time remaining: About 3 minutes	
	Go Back Continue)

11.คลิก **Close**





About This Mac		
System Preferences		
Location	•	
App Store	3 new	
Recent Items	►	
Force Quit Finder	てなまり	
Sleep		
Restart		
Shut Down		
Log Out HotLine	企業Q	

13.คลิกที่ **Printers & Scanners**

•••	< [>]		System P	Preferences		Q Search	8
File		0500	.		Ó		
General	Desktop & Screen Saver	Dock	Mission Control	Language & Region	Security & Privacy	Spotlight	Notifications
		0				4	
CDs & DVDs	Displays	Energy Saver	Keyboard	Mouse	Trackpad	Printers & Scanners	Sound
	@	5		*	*		
iCloud	Internet Accounts	Extensions	Network	Bluetooth	Sharing		
11			Ŷ			(
Users & Groups	Parental Controls	App Store	Dictation & Speech	Date & Time	Startup Disk	Time Machine	Accessibility

14.คลิกที่ +

$\bullet \bullet \circ \bullet \bullet \bullet \bullet$	Printers & Scanners	Q Search
Printers Epson AcuLaser C290 • Offline Epson AcuLaser CX1. • Offline EPSON AL-C3900 • Offline EPSON L1300 Series • Offline EPSON L1300 Series • Offline EPSON L1800 Series • Offline EPSON L200 • Offline EPSON L220 Series • Offline EPSON L310 Series	Epson AcuL Open Prin Options & Location: admin's MacBe Kind: Epson AcuLas Status: Offline	Asser C2900 ht Queue Supplies ook Pro er C2900 v3018.102 PS work Sharing Preferences
	Default printer: Last Printer	r Used
	Default paper size: A4	• • • • • • • • • • • • • • • • • • • •

15.คลิกที่ **Add Printer or Scanner**

Add Printer or Scanner
Nearby Printers
EPSON AL-C3900 @ admin's MacBook Pro
EPSON L365 Series @ admin's MacBook Pro
EPSON L565 Series @ admin's MacBook Pro
EPSON L800 @ admin's MacBook Pro
EPSON LQ-310 @ admin's MacBook Pro
EPSON Stylus Photo R230 @ admin's MacBook Pro

16.คลิกที่ EPSON L655 Series USB และคลิก Add

• • •	_	Add	
🔒 豰 i		Q	Search
Default IP W	indows		Search
Name		~	Kind
L455 (Remote)			EPSON Remote Print
FAX L655 Serie	es (USB)		EPSON FAX
EPSON Stylus	Photo R230 @ admin's Ma	cBook Pro	Bonjour
EPSON LQ-31	0 @ admin's MacBook Pro		Bonjour
EPSON L800 @	admin's MacBook Pro		Bonjour
EPSON L655 S	eries		USB
EPSON L565 S	Series @ admin's MacBook	Pro	Bonjour
EPSON L365 S	Series @ admin's MacBook	Pro	Bonjour
EPSON AL-C3	900 @ admin's MacBook P	ro	Bonjour
Name:	EPSON L655 Series		
Location:	admin's MacBook Pro	•	
Use:	EPSON L655 Series		\$
			Add

17.จะแสดงรุ่น EPSON L655 Series ขึ้นมา

••• • • •	Printers & Scanners	Q Search
EPSON L310 Series • Offline EPSON L310 Series 2 • Offline EPSON L365 Series • Offline EPSON L565 Series • Offline EPSON L655 Series • Idle, Last Used EPSON L800 • Offline EPSON L850 Series • Offline EPSON L9310 • Paused + -	EPSON L655 Open Prin Options & Location: admin's MacBe Kind: EPSON L655 S Status: Idle	5 Series It Queue Supplies ook Pro Series vork Sharing Preferences
	Default printer: Last Printer	· Used
	Default paper size: A4	?